

You will need to format a 1 or 2 GB SD card in order to perform the update.

Please back up the SD card before you format it. Formatting the card **completely erases** everything on the SD card.

1

Turn the POV Recording unit on by pressing the power button

2

Press the SETTINGS button to enter the settings menu.


3

Press the left (PREV) or the right (NXT) soft key until the settings menu gives you an option to format the SD card.


4

Press the SELECT KEY. Next press the right (NXT) soft key to change the selection to YES, when it is highlighted in red press the select key.


The screen will display "FORMATTING".




When the settings menu reappears connect the POV to the computer via a USB cable.



Double click the V1_4Upgrade DMG file. This will mount the image to your desktop (below).




Depending on your settings your computer may open the image automatically. If the image does not open double click on the icon.



Follow the directions listed above/on the image to transfer the .elf file to the SD card.



Depending on how your Mac has been configured you may see this screen. Click **Open** to continue.



After you run the command file this **Terminal** screen will appear. If the process was successful please power the POV off and then disconnect the USB cable.

Now that you have placed the .elf file on the SD card please remove the SD card from the POV Recording unit and lock it.

To do this move
this tab down to
put the SD card
into the locked
position.



Next you will have to flash the firmware on the POV Recording Unit

1

First you will have to press and hold the **SETTINGS** button. Hold is the button until the third step.

2

Next power the POV on. Press the power button once, while still holding the **SETTINGS** button.


3

The indicator light will flash. You may now stop pressing the **SETTINGS** button.

4

Once the light has stopped flashing you may remove the SD card and your firmware will be updated.

INDICATOR LIGHT



SELECT KEY

SETTINGS

POWER